




Таблицы подбора мотор-вариаторов серии МК

Вариаторы, мотор-вариаторы серии МК(F)

kW ₁ HP ₁	max	min	min	max			Poli Poles Полюс	
	n ₂ min ⁻¹	n ₂ min ⁻¹	M ₂ Nm	M ₂ Nm				
0,12	610	115	1,5	3,5	MK 2	H63b/6	6	9
	880	170	1,2	3,5	MK 2	H63a/4	4	8
0,18	660	120	2,1	8	MK 5	H71b/6	6	18
	880	170	1,6	3,5	MK 2	H63b/4	4	9
	1750	360	0,8	3	MK 2	H63b/4	2	8
0,25	660	120	2,9	8	MK 5	H71b/6	6	18
	1000	190	1,9	8	MK 5	H71a/4	4	17
	880	170	2,2	3,5	MK 2	H63c/4	4	9
	1750	360	1,1	3	MK 2	H63b/2	2	8
0,37	660	120	4,4	15	MK 10	H80a/6	6	29
	1000	190	2,8	8	MK 5	H71b/4	4	17
	660	120	4,4	8	MK 5	H71c/6	6	18
	1750	360	1,6	3	MK 2	H63c/2	2	8
0,55	660	120	6,5	15	MK 10	H80b/6	6	30
	1000	190	4,3	15	MK 10	H80a/4	4	28
	2000	380	2,2	6	MK 5	H71b/2	2	18
0,75	660	120	8,7	30	MK 20	H90Sa/6	6	50
	1000	190	5,8	15	MK 10	H80b/4	4	30
	2000	380	2,8	6	MK 5	H71c/2	2	18
1,1	1000	190	8,6	30	MK 20	H90Sa/4	4	51
	660	120	1,3	30	MK 20	H90Sa/4	6	54
	2000	380	5,8	12	MK 10	H80b/2	2	30
1,5	660	120	17	50	MK 30	H100La/6	6	88
	1000	190	11,5	30	MK 20	H90Lb/4	4	52
	2000	380	5,8	25	MK 20	H90Sa/2	2	51
	2000	380	5,8	12	MK 10	H80c/2	2	30
1,8	660	120	13,8	30	MK 20	H100Lb/6	6	53
	660	120	27	50	MK 30	H100Lb/6	6	87
	660	120	22	72	MK 50	H100Lb/6	6	90
2,2	2000	380	8,6	25	MK 20	H90Lb/2	2	53
	1000	190	17	50	MK 30	H100La/4	4	84
	660	120	26	72	MK 50	H100Ma/6	6	102
3	1000	190	23	50	MK 30	H100Lb/4	4	88
	1000	190	23	72	MK 50	H100Lb/4	4	90
	666	120	35	160	MK 100	H132Sa/6	6	155
4	1000	190	31	72	MK 50	H112Mb/4	4	100
	660	120	48	160	MK 100	H132Mb/6	6	160
5,5	666	120	65	160	MK 100	H132Mc/6	6	165
	1000	190	43	160	MK 100	H132Sa/4	4	150
7,5	1000	190	58	160	MK 100	H132Mb/4	4	160
9,2	1000	190	72	160	MK 100	H132Mc/4	4	165
11	1000	190	86	160	MK 100	H132Md/4	4	170